

New functions and addendum

Due to software upgrade, the following functions have been added and changed to this product.

• Firmware Ver.1.031fM

1. A manual pairing function has been added **PR201** **PR204**

Until now, the receiver side unit has automatically detected the camera side unit using the automatic pairing function. Now, the manual pairing function has been added so that the camera side unit to be connected to can be manually specified. This document describes the procedures to configure manual pairing as well as the procedures to revert back to automatic pairing.

■ Configuring manual pairing

When the receiver side unit cannot automatically pair to the camera side unit, use manual pairing.

- * Automatic pairing may not be able to be used when a receiver side unit that is connected to a long coaxial cable is operated together with other receiver side units.
- * For information about how to display the maintenance screen, refer to "Maintenance Screen of coaxial - LAN converter" in the Operating Instructions.
- * Before configuring manual settings for the receiver side unit, connect the receiver side unit to the camera side unit and turn on the power. Turn off the power for the other receiver side units.



①

If you use Pairing function, you can configure the camera side units to allow connection to the receiver side unit.
Please select radio button. And if you allow specified camera side units, please register the camera side units.

[Pairing Configuration]機能を使用してカメラ側機とレシーバ側機のペアリングを固定することができます。
[Camera side unit set by following...][チェックを入れて、カメラ側機のMACアドレスを登録してください]。

Note: When operating the "Back" or the "Refresh" button on the browser and clicking

"Cancel" button, the settings while editing will be discarded.

Note: Please separate six groups by hyphens "-", when Mac address is typed in.

(e.g. BC-C3-42-**-**-**)

Note: Click the [Set] button to apply settings.

注: ブラウザの[戻る][更新]操作をしたり、[Cancel]ボタンをクリックすると、設定中の内容はクリアされます。

注: MACアドレスを入力する際は、ハイフン“-”で区切って入力してください。

(例: BC-C3-42-**-**-**)

注: 設定が完了したら、[Set]ボタンをクリックして設定内容を確認してください。

All detected camera side units will be connected automatically.

②

Camera side unit set by following settings will be connected.

③

	Settings	Status	MAC Address
<input type="button" value="Add"/>	Not Registered	Connected	<input type="text"/>
<input type="button" value="Add"/>	Not Registered	Connected	<input type="text"/>
<input type="button" value="Add"/>	Not Registered	Connected	<input type="text"/>
<input type="button" value="Add"/>	-	-	<input type="text"/>

④

- In the maintenance screen, click [Pairing] ①
- In the [Pairing Configuration] screen, select [Camera side unit set by following settings will be connected.] ②
- Click the [Add] button to the left of the MAC address of the camera side unit to be connected to ③
 - * If a dialog is displayed, click the [OK] button.
 - * The MAC address is written on the rear side of the camera side unit. There may not be a hyphen ("-").
 - * If an unexpected MAC address is displayed, do not click the [Add] button to its left.
 - * The [Add] button changes to the [Delete] button after it is clicked.
- Click the [Set] button ④
 - * If a dialog is displayed, click the [OK] button.
 - * In the [Pairing function] screen, click the [Reset] button.

WJ-PR204

Pairing Configuration

Status

Option

Pairing

Upgrade

Restart

Copyright

If you use Pairing function, you can configure the camera side units to allow connection to the receiver side unit.
Please select radio button. And if you allow specified camera side units, please register the camera side units.

[Pairing Configuration]機能を使用してカメラ側機とレシーバ側機のペアリングを固定することができます。
[Camera side unit set by following...]にチェックを入れて、カメラ側機のMACアドレスを登録してください。

Note: When operating the "Back" or the "Refresh" button on the browser and clicking "Cancel" button, the settings while editing will be discarded.
Note: Please separate six groups by hyphens "-", when Mac address is typed in. (e.g. BC-C3-42-**-**-**)
Note: Click the [Set] button to apply settings.

注: ブラウザの[戻る][更新]操作をしたり、[Cancel]ボタンをクリックすると、設定中の内容はクリアされます。
 注: MACアドレスを入力する際は、ハイフン"-"で区切って入力してください。
 (例: BC-C3-42-**-**-**)
 注: 設定が完了したら、[Set]ボタンをクリックして設定内容を確認してください。

6 All detected camera side units will be connected automatically.
 Camera side unit set by following settings will be connected.

	Settings	Status	MAC Address
Add	Not Registered	Connected	<input type="text"/>
Add	Not Registered	Connected	<input type="text"/>
Add	Not Registered	Connected	<input type="text"/>
Add	-	-	<input type="text"/>

5. After resetting is completed, click [Pairing] in the maintenance screen ⑤

* [All detected camera side units will be connected automatically.] is selected ⑥. Confirm that "Not Registered" is displayed in the [Settings] field ⑦.